



### Main

For switching loads via a make contact. Can be remote-controlled via transmitters in the Merten CONNECT system.  
Radio features: **Router**

### Complementary

Suitable for installation into a size 60 installation box. With snap-off mounting plates.  
With screw terminals.

### Functions:

EASY CONNECT:

- Switch on, switch off, toggle

With CONNECT radio configuration tool:

- additionally staircase lighting function, ON/OFF delay

**Nominal voltage:** AC 230 V

**Nominal current:** 10 A

**Connected loads:**

**Incandescent lamps:** AC 230 V, 2000 W

**Halogen lamps:** AC 230 V, 1500 W

**Capacitive load:** 35  $\mu$ F

**Display elements:** LED for status display

**Operating elements:** Push-button for local operation and programming

**Dimensions:** 48 x 52 x 27 mm (H x W x D)